

F16

IP65 Rated Outdoor Fingerprint Access Control Terminal

F16 is a fingerprint access control terminal with an integrated proximity reader (EM). IP65 rated waterproof enclosure permits this reader to be used for outdoor applications. It could install easily on your network having both Ethernet and RS485 serial ports. Weigand-OUT port allows connection of reader to ZK or any 3rd party access control panel. Using Weigand-IN port you connect to any card reader for authentication at both entrance and exit.

PULL firmware and ZKAccess3.5 management software as standard configuration make F16 more versatile and powerful. Users can be registered on the device by the Management Card or through connecting with ZKAccess3.5 software by TCP/IP.



Features



- ▶ **Rugged structure for outdoor installation and extra durability**
- * IP65 rated waterproof and dustproof structure



- ▶ **Slim and elegant design**
- * One of the world's smallest fingerprint terminals
- * Sleek and slim design for narrow spaces



- ▶ **Fast and accurate fingerprint algorithm**
- * Fingerprint identification in 1 second
- * Stores 3,000 fingerprint templates, 30,000 cards and 100,000 transactions



- ▶ **Easy installation and connectivity**
- * Wiegand input & output
- * Network interface by TCP/IP or RS485



- ▶ **Full access control features**
- * Anti-passback
- * Access control interface for 3rd party electric lock, door sensor, exit button, alarm



- ▶ **For Software Developers**
- * Free PULL SDK and development tools are available for developers/partners


Specifications:

Fingerprint Sensor	ZK Optical Sensor
Algorithm Version	ZKFinger V10.0
Communication	TCP/IP, RS485
Fingerprint Capacity	3,000 Fingerprints
Card Capacity	30,000 Cards
Log Capacity	100,000 Transactions
RF Card	EM(standard)/Mifare(optional)
Authentication	Finger/Card
Wiegand Signal	Wiegand input&output
Ingress Protection Rate	IP65
Operating Voltage	12VDC 3A
Operating Temperature	0°C~ 45°C (32°F ~ 113°F)
Size	62.5mm × 185mm × 41.5mm (W × H × D)

Optional Accessories:



Configuration:



Application:



Networked Security:
School



Networked Security:
Building



Access Control:
Shop



Access Control:
House



Time Attendance:
Factory



Time Attendance:
Office

ZKTeco Inc.

ZK Mansion, Wuhe Rd, Gangtuo, Bantian, Buji Town, Longgang District, Shenzhen China 518129 Tel: +86-755-8960 2345/46/47/48 Fax: +86-755-8960 2675 www.zkteco.com

Global Service Hotline:

USA: +1 732-412-6007
EU: ++34 916 532 891
Brazil: +55 (31) 2515-8326
Thailand: +66-027199154
Mexico: +52-55-52078969
South Africa: +27 12 259 1047

Egypt: +202-24055541
Dubai: +971 4 6091 310
India: +91 9650971689
Indonesia: +62 21 2921 8949
Vietnam: +84-0169-5813007
Philippines: +63 9998775576

